

# WARHAWK

## ENGINEERED AUTOMATIC DOOR SOLUTIONS



### **POWER SUPPLY TRANSFORMER TO MAINS**

**Main Power:**

**White Lead = Neutral**

**Black Lead = 115VAC (HOT)**

### **POWER SUPPLY BOARD TO ELECTRIC STRIKE**

**SET SW2 Located On Power Supply Board To "Open", This will output 12VDC**

**AUX + Terminal Connect To RED/BLACK +12 (Electric Strike)**

**COM - Terminal Connect To BLUE/GREEN (Electric Strike)**

### **POWER SUPPLY BOARD TO KEY PAD**

**AUX + Terminal Connect To Red Wire (POWER IN)**

**AUX - Terminal Connect To Black Wire (GROUND)**

**NO TRIG Connect To Blue Wire (RELAY NO)**

**GND INPUT Connect To Purple Wire (RELAY COMMON)**

# WIRING MATRIX

## ELECTRIC LOCK & CARD READER